Digital Thermometer User instruction

FEATURES:

- . IP66 Waterproof design.
- . Resolution: 0.1°.
- Measurement range: -50°C to 300°C (-58°F to 572°F).
- Measurement accuracy: 1°C (2°F) at -20°C to 150°C (-4°F to 302°F).
- The large, bright backlit light can be turned on and off or set to auto-off in 10 seconds.
- A strong internal magnet allows the thermometer to be stuck on metal surfaces.
- The LCD will display low battery icon when the power is low.
- Hold temperature function to stop the display from changing the read out.
- The thermometer will automatically turn off after 10 minutes if no other buttons are pressed.



Digital Thermometer User instruction

OPERATION:

- 1. Before using the thermometer, please peel off the protective film from the LCD.
- 2. To turn ON the thermometer, press the 🎥 button for 2 seconds. The LCD screen will turn on and will shortly display all the options and then the current probe temperature.
- 3. The default display unit is Fahrenheit. To change it to Celsius, please press the button for 2 seconds.



- 4. Data-hold: before withdrawing from chemicals press the button. This will hold the temperature reading until pressed again.
- 5. To light up the LCD display, press the 🦺 button once. When the backlight turns on, press the button again to turn off. The backlight will turn off automatically after 10 seconds if no button is pressed.

